



## FEATURES:

- Fits standard 19" (483 mm) racks
- Supports up to 4 microphone inputs
- Phantom power for condenser type microphones.
- Inputs can be mixed/mapped to any combination of up to 4 output channels.
- Light weight, compact and durable.
- Compatible with all FTR audio recording applications.

**The FTR MX4+ Audio Mixer** is a compact and lightweight audio mixer unit that's well suited for applications where space is limited, and portability and rapid set-up are important. It supports up to 4 microphone inputs and can supply phantom power for condenser type microphones. Each of the 4 inputs can be mixed/mapped to any combination of up to 4 output channels. The MX4+ accommodates either balanced or unbalanced inputs and has selectable 120/240-volt power.

The MX4+ audio mixer is simple to use and ideal for courts that need excellent audio performance and reliability, but have limited space or require portability. It's easy to set up and operate because it arrives preconfigured for 4-channel operation and ready to work with conventional dynamic microphones. Microphones 1 through 4 are mapped to output on channels 1 through 4, respectively, and phantom power is disabled. These features make the MX4+ a perfect choice for capturing the record whether you're recording a trial in the courtroom down the hall or off-site.

## MX4+ Audio Mixer Front Panel



## How the MX4+ Audio Mixer Helps Your Court Function More Efficiently



**ForTheRecord®**

### VERSATILE!

- Fits standard 19" (483 mm) racks.
- Supports up to 4 microphone inputs and can supply phantom power for condenser type microphones.
- Each input can be mixed/mapped to any combination of up to 4 output channels.
- Selectable 120/240-volt power.
- Accommodates balanced or unbalanced inputs.
- Ideal for applications where space is limited and portability and quick set up are important.
- Compatible with all FTR audio recording applications.



### SPECIFICATIONS

Input/Output	Default	Minimum	Maximum	Notes
Microphone Input	-70dBV	-70dBV	-52dBV	Input impedance 2K $\Omega$
Auxiliary Output (DB9)	+4dBm	-10dBm	+10dBm	Output impedance 600 $\Omega$
Line Output (RCA)	-4dBV	-13dBV	+2dBV	Output impedance 10K $\Omega$

### Overall Response (any input to any output)

Frequency Response	-3dB	100Hz	7.5kHz	
Signal/Noise Ratio			-65dB	Un-weighted

### Dimensions

Metric	189mm x 40mm x 199mm	Weight – 1 Kg
English	7.4" x 1.6" x 8"	Weight – 2.2 lbs.

### General

Mains Power	120 or 240 volts AC ( $\pm$ 10%), 50 or 60 Hz (*)
Fuse	For 120V operation, use Bussmann GMC series 125mA or Bussmann S504 Series 125mA. For 240V operation, use Bussmann S504 Series T50mA.
Ambient Environment	0 to 30 °C, 10 to 90% humidity (non-condensing)

(\*) The mixer is voltage selectable for different regions.

**AUTHORIZED RESELLER:**

### FTR Limited

2901 North Central Avenue  
Suite 400  
Phoenix, Arizona 85012 USA  
tel. 602.650.0958  
fax 602.385.4990  
toll-free 877.650.0958

### FTR PTY LTD

16 Brodie Hall Drive  
Suite 7  
Technology Park  
Western Australia  
6102 Australia  
tel. 61.8.9470.4366  
fax 61.8.9470.4310